**WARNING!**

THIS DRAWING IS FOR USE WITH VAN'S AIRCRAFT SUPPLIED KITS. CAREFULLY COMPARE THIS DRAWING TO YOUR KIT BEFORE BEGINNING INSTALLATION. NOTIFY VAN'S AIRCRAFT IMMEDIATELY IF ANY DISCREPANCIES EXIST. THIS DRAWING IS NOT INTENDED TO BE USED AS A STAND-ALONE DOCUMENT. REFER TO ASSOCIATED INSTALLATION MANUALS FOR ADDITIONAL INFORMATION AND DETAILS. FAILURE TO FOLLOW THESE INSTRUCTIONS MAY RESULT IN DAMAGE TO EQUIPMENT, INJURY, OR DEATH. VAN'S AIRCRAFT, INC. ASSUMES NO RESPONSIBILITY FOR ANY DAMAGE CAUSED BY ERRORS, OMISSIONS OR MISINTERPRETATIONS OF THIS DRAWING OR ANY ASSOCIATED INSTALLATION MANUALS. THE CUSTOMER ASSUMES ALL RISK AND LIABILITY ARISING FROM THE USE OF THIS DRAWING AND ASSOCIATED MANUALS.

CIRCUIT LETTER FUNCTION | DRAWING KEY

| LETTER | FUNCTION |
|---|---|
| A | GROUND |
| B | +12V, +14V, +28V |
| C | AUDIO, COMMUNICATION |
| D | DISCRETE SIGNALS |
| E | DIGITAL SIGNALS |
| F | ANALOG SIGNALS |
| G | LIGHTING |
| H | SPARE |
| I | SPARE |
| J | SPARE |
| K | SPARE |

VAN'S AIRCRAFT, INC.

NXXXXX

ELECTRICAL SYSTEM

RV-XX

DRAFT: IN WORK

DRAWN BY: XXXX

TOLERANCES: NONE

SCALE: NONE

UNLESS OTHERWISE SPECIFIED

DATE: XX/XX/XX

AIRCRAFT SERIAL NO.: XXXXX

FILENAME: XXXXXXX

14401 NE 31ST CIR, RIDGEFIELD WA 98642 USA

DO NOT SCALE DRAWING